

# **RB 2000**

Light Commercial & Commercial Regulator

The RB 2000 regulator is designed for applications and for all installations with continuous consumption or rapid flow rate variations, such as burners, industrial ovens, boilers, etc.

It is suitable for installation in cabinets, as a space saving regulator.

#### **KEY BENEFITS**

- » Balanced valve design eliminates inlet pressure effect
- » Rugged construction for durability
- » Rapid response to load changes
- » Built-in shut-off valve
- » Internal relief
- » Inlet strainer

#### **DESCRIPTION**

The RB 2000 regulator is a direct-acting, spring-loaded regulator (lever type) with a built-in relief valve and optional safety shut-off device.

The balanced valve ensures constant outlet pressure when the upstream pressure varies.

This eliminates changes to the orifice size arising from different inlet pressure ranges.

The regulator is equipped with a built-in filter (filtration grade 0.5 mm).

The safety shut-off valve cuts the gas flow when the outlet pressure exceeds the set pressure (OPSO) or when it drops below the set value (UPSO). It remains closed until the valve is reset manually.

The relief valve avoids triggering the safety shut-off valve in case of thermal expansion, transient surges of pressure, and creep leaks from the regulator. The relief pressure is pre-set at the factory.

#### **Technical Features**

recimioari catares					
Maximum inlet pressure	10 bar				
Outlet pressure	5 mbar - 180 mbar - Extended range up to 750 mbar				
Accuracy & lock-up pressure	Up to AC5 / up to SG 10				
Operating temperature	-20°C to +60°C				
Ambient temperature	-30°C to +60°C (body material)				
Acceptable gases	Natural gas, town gas, propane, butane, air, nitrogen or any non- corrosive gas				
Installation	Horizontal or vertical				
Safety devices	Standard relief valve Optional built-in safety shut-off valve: - over-pressure shut-off (OPSO) - under-pressure shut-off (UPSO)				
Options	Internal or external sensing line Monitor version				

## Sizes & Connections

Sizes


Type

.71		
Materials		
Body	Spheroidal graphite iron EN 1563 grade EN-GJS-400-15	
Head	Die cast aluminium	
Internal parts	Stainless steel and brass	
Seals	Nitrile rubber	
Diaphragm	Rubberized fabric	

Parallel internal thread according to ISO 228/1 or ISO 7/1

1" x 1" - 1" x 1"½

# **Operational Diagram**



# **TYPE DESIGNATION AND OPTIONS**

To specify the version of the RB 2000 regulator to be ordered, select the options and relevant codes from the table below.

R	В	X	2	X	1	X	X	X	Variants
		Ε							External sensing line
		1							Internal sensing line
				3					Size 1"x 1"
				6					Size 1" x 1"1/2
						0			Relief valve
						1			Relief valve + Over-pressure shut-off valve
						2			Relief valve + Over and low-pressure shut-off valve
							Μ		Monitor version
								TR	Reduced head (see spring selection tables)

 $\textbf{Example:} \ RBE\ 2312/TR\ is\ a\ 2300\ regulator\ with\ a\ balanced\ valve,\ an\ external\ sensing\ line,\ a\ reduced\ head\ an\ an\ OPSO/UPSO\ shut-off\ valve.$ 

#### **OUTLET PRESSURE RANGE**

#### Regulator

guiatoi							
		Spring Ch	aracteristic	;	Spring Range		
Spring Code	d De Lo Lt (mm) (mm)		2300-2600	2300-2600 TR			
20564241	1.5	30	80	9.5	6 - 10 mbar	•	
20564141	1.6	30	80	9.5	8 - 13 mbar	•	
20564142	1.8	30	80	8.5	13 - 25 mbar	•	
20564050	1.8	30	100	10	20 - 28 mbar	•	
20564051	2	30	100	11.5	26 - 39 mbar	•	
20564044	2.2	30	80	9	36 - 50 mbar	•	
20564042	2.5	30	80	9	46 - 80 mbar	95 - 215 mbar	
20564043	2.5	30	80	7	80 - 110 mbar	180 - 260 mbar	
20564143	3	30	80	9	100 - 180 mbar	260 - 400 mbar	
20564144	3.5	30	80	9	•	450 - 750 mbar	

## Safety Shut-off Valves

# **Over-Pressure Shut-off Springs (OPSO)**

When Also Fitted With UPSO Spring\*

		Spring Ch	aracteristic	;	Spring Range		Spring Range	
Spring Code	<b>d</b> (mm)	<b>De</b> (mm)	<b>Lo</b> (mm)	Lt	2311-2611	2311-2611 TR	2312-2612	2312-2612 TR
20563022	1.5	25	35	5.5	20 - 60 mbar	•	28 - 60 mbar	•
20563023	1.7	25	35	5.5	30 - 90 mbar	90 - 130 mbar	40 - 90 mbar	90 - 130 mbar
20563014	1.9	25	35	5.5	60 - 130 mbar	120 - 180 mbar	70 - 130 mbar	120 - 180 mbar
20563124	2.2	25	35	5.5	70 - 220 mbar	160 - 330 mbar	120 - 220 mbar	160 - 330 mbar
20563121	2.5	25	35	5.5	150 - 400 mbar	300 - 600 mbar	220 - 420 mbar	300 - 600 mbar
20563115	3	25	35	5.5	•	580 - 1000 mbar	•	580 - 1000 mbar

 $<sup>^{\</sup>star}$  the space available for the OPSO spring is reduced by the UPSO spring assemblly

#### **Under-Pressure Shut-off Springs (UPSO)**

		Spring Ch	aracteristic		Spring Range		
Spring Code	<b>d</b> (mm)	<b>De</b> (mm)	<b>Lo</b> (mm)	Lt	2312-2612	2312-2612 TR	
20560522	0.7	10	20	7	4 - 14 mbar	•	
20560511	0.8	10	20	7	10 - 25 mbar	•	
20560515	0.8	10	30	10	20 - 27 mbar	•	
20560518	0.9	10	30	10	37 - 45 mbar	•	
20560516	1	10	30	10	•	26 - 57 mbar	
955-201-17	0.9	10.4	28	7	•	13 - 50 mbar	
20560520	1	10.3	25	7.5	45 - 75 mbar	•	
20560521	1.3	15	40	9.5	•	60 - 90 mbar	
20560517	1.2	10	30	10	•	85 - 170 mbar	
20560519	1.4	10	30	10	•	150 - 300 mbar	

#### **Relief Valve**

The built-in relief valve is set 15 mbar (head 180) or 50 mbar (head 180 TR) above the outlet pressure setting. Other settings on request.

# Spring characteristics:

d: wire diameter Lo: height
De: external diameter Lt: no. of spires

#### **FLOW CAPACITY**

Inlet Pressure	Capacities in m³/h at Standard Conditions Outlet Pressure Setting						
	20 mbar	50 mbar	100 mbar	300 mbar	500 mbar		
RBI 2312 - 1"x 1" (with SSV)							
0.35 bar	70	80	70	-	-		
0.5 bar	90	95	90	50	-		
0.7 bar	65	115	110	70	-		
1 bar	40	120	130	100	80		
1.5 bar	35	110	130	140	130		
2 bar	35	110	130	150	150		
4 bar	35	80	120	150	170		
8 bar	35	80	110	115	190		
RBI 2612 - 1"x 1"1/2 (with S	SV)						
0.35 bar	65	80	65	-	-		
0.5 bar	90	95	80	50	-		
0.7 bar	115	120	115	75	-		
1 bar	115	130	130	110	90		
1.5 bar	90	130	130	150	130		
2 bar	115	130	130	180	170		
4 bar	100	130	130	180	200		
8 bar	80	130	130	180	200		

Maximum capacities at 20% drop or boost.

» The values given are those for appropriately sized pipe work.

# **FLOW CAPACITY**

The wide-open flow capacity may be calculated using the following formula:

» In critical flow conditions: If  $(P_U - P_d) > 2$  Q = 160  $P_U/2$ 

» In non-critical flow conditions: If  $(P_u - P_d) \le 2$  Q =  $160\sqrt{P_d(P_u - P_d)}$ 

#### Standard conditions:

- Absolute pressure of 1.013 bar
- Temperature of 15°C

# Correction factor for non-natural gas applications:

The flow rates are indicated for a 0.6 specific gravity gas.

To determine the volumetric flow rate for gases other than natural gas, multiply or calculate the values in the capacity tables using the sizing equations with a correction factor.

The table below lists correction factors for some common gases:

Gas type	Specific gravity	Correction factor
Air	1.00	0.77
Butane	2.01	0.55
Carbon dioxide (dry)	1.52	0.63
Carbon monoxide (dr	y) 0.97	0.79
Natural gas	0.60	1.00
Nitrogen	0.97	0.79
Propane	1.53	0.63
Propane-Air mix	1.20	0.71

Specific gravity or relative density (air = 1, non-dimensional value)

Use the following formula to calculate the correction factor for gases not listed above. In the formula, d is the specific gravity of the gas.

Correction factor =  $\sqrt{\frac{0.6}{d}}$ 


#### where:

Q = maximum flow capacity (Sm<sup>3</sup>/h)


 $P_u$  = absolute inlet pressure in bar

 $P_d$  = absolute outlet pressure in bar

# **OVERALL DIMENSIONS** (mm)




RB 2000 Without Safety Shut-off Valve - Weight 2 kg




Sensing line (regulator and SSV) tapping threaded Rp 1/4 fitted with compression fitting for 8 mm pipe

#### **INSTALLATION**

- » The RB 2000 regulator can be mounted in any horizontal or vertical position
- » RB 2000 can be used as monitor regulator, upstream from an active regulator.
  - In that case, the external sensing line must be connected downstream from the regulator to be controlled.



RB 2000 With Safety Shut-off Valve - Weight 2.5 kg



# Information to be specified when ordering:

- » Regulator type code
- » Minimum and maximum inlet pressures
- » Outlet pressure range setting
- » Outlet pressure setting
- » Maximum flow rate
  - OPSO setting\*
  - UPSO setting\*

\* (if requested)



Join us in creating a more **resourceful world**.

To learn more visit **itron.com** 

While Itron strives to make the content of its marketing materials as timely and accurate as possible, Itron makes no claims, promises, or guarantees about the accuracy, completeness, or adequacy of, and expressly disclaims liability for errors and omissions in, such materials. No warranty of any kind, implied, expressed, or statutory, including but not limited to the warranties of non-infringement of third party rights, title, merchantability, and fitness for a particular purpose, is given with respect to the content of these marketing materials. © Copyright 2014 Itron. All rights reserved. **GA-RB2000-04-EN-10-14** 

#### ITRON GmbH

Hardeckstraße 2 D-76185 Karlsruhe Germany

**Phone:** +49 (0) 721 5981 0 **Fax:** +49 (0) 721 5981 189